

120 VAC ARM LIGHT FLASHER Specifications



120 VAC FLASHER

GENERAL: The flasher shall be moisture and corrosion resistant and shall be capable of dissipating heat sufficient for continuous duty.

FLASH RATE: The flasher shall have two alternately flashing circuits. Each circuit shall flash .50 seconds on and .50 seconds off.

INPUT VOLTAGE: Standard input voltage shall be 120VAC. The flasher shall operate properly for input voltages within 10% of nominal.

OUTPUT VOLTAGE AND AMPERAGE: The circuits shall be rated at 10 amps at 120VAC each (10 amps total load). A voltage drop of up to 6 volts to the output terminals shall be acceptable.

FUSE: Fuse shall be 10 amp, 250 Volt, fast-acting, cartridge-type, ¼" diameter, 1 ¼" long, UL and/or CSA approved.

TERMINALS: Terminals shall be clearly labeled and shall be compression type screw terminals.

Revised 03/06